



DESCRIPTION:

- SINGLE CIRCUIT, TWO RELAY LIGHTING CONTROL WITH DIMMING, RESTRICTED TO MANUAL ON, FULL AUTO OFF, MANUAL OFF
- AUTOMATIC RECEPTACLE CONTROL
- CEILING OCCUPANCY SENSOR(S), LOW-VOLTAGE SWITCH(ES)

NOTES:

- PROVIDE ONE ROOM CONTROLLER FOR THE SET OF LUMINAIRES IN THE ROOM DESIGNED TO BE CONTROLLED SEPARATELY, OR FOR EACH CIRCUIT TO BE CONTROLLED. PROVIDE ONE SINGLE-RELAY ROOM CONTROLLER FOR EACH CIRCUIT FOR RECEPTACLE CONTROL. PROVIDE ONE OCCUPANCY SENSORS AS INDICATED ON PLANS. PROVIDE ONE OR MORE LOW-VOLTAGE SWITCHES FOR EACH SPACE TO BE CONTROLLED. SEE PROGRAMMING NOTES.
- PROGRAMMING OF LOAD CONTROL BUTTONS: ON LEFT SIDE, PROGRAM THE TOP TWO (2) BUTTONS AS RAISE/ON (AT 100% PRESET LEVEL) - LOWER/OFF CONTROLS FOR DIMMABLE LIGHTING LOAD 'a' AND BOTTOM TWO (2) BUTTONS AS RAISE/ON (AT 100% PRESET LEVEL) - LOWER/OFF CONTROLS FOR DIMMABLE LIGHTING LOAD 'b'. ON THE RIGHT SIDE, PROGRAM ALL FOUR (4) BUTTONS AS SCENE SELECTION BUTTONS IN ACCORDANCE WITH USER DIRECTION.
- IT IS THE INTENT OF THIS WIRING DIAGRAM TO REPRESENT SITUATIONS INVOLVING LUMINAIRES WITH MULTIPLE LIGHT LEVELS (FULL-DIMMING).

SEQUENCE OF OPERATION:

- LIGHTING SYSTEM TURNS "ON" WHEN LOW-VOLTAGE SWITCH IS OPERATED.
- CONTROLLED RECEPTACLES TURNS "ON" WHEN SENSOR DETECTS OCCUPANCY.
- LIGHTING SYSTEM TURNS "OFF" WHEN LOW-VOLTAGE SWITCH IS OPERATED, OR ENTIRE SYSTEM TURNS "OFF" (LIGHTING AND CONTROLLED RECEPTACLES) WHEN OCCUPANCY SENSORS NO LONGER DETECT THAT THE ROOM IS OCCUPIED AND THE PROGRAMMED TIME DELAY HAS ELAPSED.

GENERAL NOTES: (APPLICABLE TO ENTIRE SHEET)

- VERIFY WIRING REQUIREMENTS WITH MANUFACTURER. WIRING MAY DIFFER BETWEEN MANUFACTURERS.
- FOR QUANTITY OF SENSORS AND SWITCHES, REFER TO LIGHTING PLANS.
- AUTOMATIC LIGHTING CONTROL SYSTEM MUST COMPLY WITH NFPA 101, 7.8.1, TO INCLUDE BUT NOT LIMITED TO THE FOLLOWING:
 - THE AUTOMATIC LIGHTING CONTROL DEVICE MUST BE LISTED.
 - THE AUTOMATIC LIGHTING CONTROL MUST BE EQUIPPED TO AUTOMATICALLY ENERGIZE THE CONTROLLED LIGHTS UPON LOSS OF NORMAL POWER. SEE FIRE PROTECTION DRAWINGS FOR REQUIREMENTS.
- THE AUTOMATIC LIGHTING CONTROL DEVICE IS ACTIVATED BY OCCUPANT MOVEMENT IN THE AREA SERVED.
- THE AUTOMATIC LIGHTING CONTROL DEVICE IS ACTIVATED BY ACTIVATION OF THE BUILDING FIRE ALARM SYSTEM.
- THE AUTOMATIC LIGHTING CONTROL DEVICE DOES NOT CAUSE THE DE-ENERGIZING OF EMERGENCY BATTERIES.
- PROVIDE ALL CONDUIT, WIRING DEVICES, AND CONNECTIONS REQUIRED.
- SUBMIT SHOP DRAWING OF ENTIRE SYSTEM, TO INCLUDE BUT NOT LIMITED TO PRODUCT DATA AND WIRING/CONTROL DIAGRAMS FOR REVIEW AND APPROVAL.
- INSTALL ALL CABLES IN CONDUIT. MINIMUM CONDUIT SIZE AS PER SPECIFICATION 16402.

CONTROLS WIRING DIAGRAM (WD03R)

IF SHEET IS LESS THAN 24" X 36"
REDUCED PRINT - USE GRAPHIC SCALES

REVISIONS		
No.	Description	Date

TRMA

Taniguchi Ruth Makio Architects

100 Cliff Business Center, P.O. Box EA, Agaña, GU 96910

Tel.: (671) 475-8772 • Fax.: (671) 472-3381

Architecture
Planning
Interior Design

eme

EMCE • Consulting engineers

SUITE 201, 133 ANTONIA COURT

P.O. BOX 8888 TAMUNING, GUAM 96931

671 . 649-0166/7 Phone

671 . 646-EMCE (3623) Fax

PROF. V. MARIANO

REGISTERED PROFESSIONAL ENGINEER

373

STATE OF NORTHERN MARIANA

I HEREBY CERTIFY THAT THIS PLAN WAS PREPARED BY ME OR UNDER MY DIRECT SUPERVISION

Abra V. Mariano

DATE: 10/7/2022

Project:

NMC
PACKAGE 1: STUDENT
CENTER BUILDING

Title:

MISCELLANEOUS
DIAGRAMS - SHEET 4

CONSTRUCTION
DOCUMENTS

Designed: JF/LB
Drawn: NP/RS
Checked: IA/AM
Supv: AM
Scale: AS INDICATED
Date: 10/07/2022
Project No. File

Drawing No.
E2.8
Sheet No. _____ of _____